# SD NAND ŨỸ ^ 9˜ ®



| Bits | Description | Width |
|---|---|---|
| 379:376 | mode 0 - The function which can be switched in function group 1.<br>mode 1 - The function which is result of the switch command, in function group 1. 0xF shows function set error with the argument. | 4 |
| 375:368 | Data Structure Version<br>00h – bits 511:376 are defined<br>02h-FFh = reserved | 8 |
| 367:352 | Reserved for Busy Status of functions in group 6.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 351:336 | Reserved for Busy Status of functions in group 5.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 335:320 | Reserved for Busy Status of functions in group 4.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 319:304 | Reserved for Busy Status of functions in group 3.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 303:288 | Busy status of functions in group 2.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 287:272 | Reserved for Busy Status of functions in group 1.<br>If bit [i] is set, function [i] is busy. This field can be read in mode 0 and mode 1 | 16 |
| 271:0 | Reserved (All '0') | 272 |

杭州瀚海微科技有限公司
www.hanhai-tech.com

ŵ ß Â ч ˘ h
Ь ˊ Â ע Ɒ ˘ ɢ ˊ Â

₱ خي ƀ Ţ ® ˘ ғ خيف Ţ نج ╠ ₱ ˍ˘ ↕ ч ₱ Â
ƀ ٦ ψ ف ₱ ч Â

| Argument | Busy Status | Status Code | Comment |
|---|---|---|---|
| 0 | Don't Care | 0 | Default function can always be switched. |
| Supported function | Ready | =Arg. | Status indicates the same function number as specified in the argument, which means successful function change. |
| [illegible] | [illegible] | Busy | Current Selected [illegible] current selected function. |
| [illegible] | Not Supported function | Don't Care | Fh | If one of the function groups in code Fh, switch requests to all are canceled and the rest of Status Data Structure should be |
| function | Fh | Don't Care | Current Selected | Status indicates current selected |

**Status Code of Mode 1 to Supported Function Group**

| Argument | Busy Status | Status Code | Comment |
|---|---|---|---|
| Status always indicates 0. | | 0 | Don't Care | 0 |
| Status always indicates Fh. | | Eh-1h | Don't Care | Fh |
| Status always indicates 0. | | Fh | Don't Care | 0 |

**Status Code of Mode 0 and 1 to Unsupported Function Group**

杭州瀚海微科技有限公司
www.hanhai-tech.com